

# **ANALOG WAY LIVEPREMIER™**

## **Module: IMAGESLIBRARY**

### **Crestron 3-series & 4-series**

Date: **July 19th 2021**  
Driver version: **V2.2.0**  
Compatible with: **LivePremier™ Firmware V2.0.231 or above**

## **GENERAL**

This module retrieves LivePremier™ images library status and provides its related control.

## Control

### General

AW_ImgLib_RefreshInfos	Digital_in	Pulse this signal to force information retrieval. Most of the time this signal is never use
------------------------	------------	---

### Status

AW_ImgLib_Valid_FB[X]	Digital_out	For each image slot: Equals 1 when an image slot is valid, 0 otherwise
AW_ImgLib_Used_FB[X]	Digital_out	For each input: Equals 1 when an image slot is associated with one image, 0 otherwise

### Source

AW_ImgLib_ImageAffectation_Cmd[X]	Analog_In	The index of the image that will be associated to slot X.
AW_ImgLib_ImageAffectation_FB[X]	Analog_Out	The index of the image that is associated to slot X.

### Capabilities

AW_ImgLib_Capabilities_FB[X]	String_Out	The image capability
------------------------------	------------	----------------------

### Format

AW_ImgLib_Format_FB[X]	String_Out	The image slot format, following the syntax: Width x Height in pixels
------------------------	------------	--

### FileName

AW_ImgLib_FileName_FB[X]	String_Out	The file name in a slot
--------------------------	------------	-------------------------